



Disconnect / Cut the Red and Black wires from the transformer and using a piece of the connector strip connect your installed cables directly to the loudspeaker.

Loudspeaker Connection

2N SIP Speaker, Wall Mounted is equipped with a power amplifier for 1 or 2 loudspeakers. The loudspeakers to be used must have the nominal impedance of 8 Ω each. Refer to the table below for possible configurations and related maximum power outputs (sinus, THD < 1 %):

Loudspeaker(s)	12 V / 2 A	PoE
Two 8 Ω	2x 9 W	2x 5 W
One 8 Ω	1x 12 W	1x 10 W